

WIRE COLOR CODE CONVERSION for B5A-13341-A & B8A-13341-A TURN SIGNAL SWITCH

Installation of switch #B5A-13341-A & #B8A-13341-A to the original wire harness must follow this color guide for proper operation.

WIRING FROM TURN SIGNAL SWITCH AND ITS' OPERATION

GREEN WIRE with RED COLLAR..... stop light switch
ORANGE WIRE with WHITE COLLAR.....right taillight
BLUE WIRE flasher & battery
GREEN WIRE with GREEN COLLAR.....left turn parking light
WHITE WIRE with YELLOW COLLAR...right turn parking light
GREEN WIRE with WHITE COLLAR.....left taillight

EXISTING
WIRE HARNESS IN
CAR WITH ORIGINAL
WIRE COLOR CODE

